



KEOR SPE RT Battery back-up times



Keor SPE RT

Line Interactive Technology

VI

Recommended for small IT application

311065 Keor SPE RT 750 (1U) 750VA / 525W (PF = 0.7)

Load %			Int.batt.	Battery Cabinets (Mins)			
%	VA	W		BATTERY CABINETS N.A. FOR THIS MODEL			
10 %	75	52	93	-	-	-	-
20 %	150	105	44	-	-	-	-
30 %	225	158	26	-	-	-	-
40 %	300	210	17	-	-	-	-
50 %	375	262	13	-	-	-	-
60 %	450	315	10	-	-	-	-
70 %	525	368	8	-	-	-	-
80 %	600	420	6	-	-	-	-
90 %	675	472	4	-	-	-	-
100 %	750	525	4	-	-	-	-

311066 Keor SPE RT 1000 (1U) 1000VA / 700W (PF = 0.7)

Load %			Int.batt.	Battery Cabinets (Mins)			
%	VA	W		BATTERY CABINETS N.A. FOR THIS MODEL			
10 %	100	70	59	-	-	-	-
20 %	200	140	29	-	-	-	-
30 %	300	210	17	-	-	-	-
40 %	400	280	12	-	-	-	-
50 %	500	350	9	-	-	-	-
60 %	600	420	6	-	-	-	-
70 %	700	490	4	-	-	-	-
80 %	800	560	3	-	-	-	-
90 %	900	630	3	-	-	-	-
100 %	1000	700	2	-	-	-	-

311067 Keor SPE RT 1000 (2U) 1000VA / 800W (PF = 0.8)

Load %			Int.batt.	Battery Cabinets (311074) (Mins)			
%	VA	W		1	2	3	4
10 %	100	80	71	289	508	710	869
20 %	200	160	36	142	284	400	541
30 %	300	240	23	96	170	272	348
40 %	400	320	14	65	119	187	271
50 %	500	400	11	53	102	150	205
60 %	600	480	9	43	83	117	163
70 %	700	560	7	34	64	103	133
80 %	800	640	5	28	55	89	114
90 %	900	720	4	25	49	76	103
100 %	1000	800	3	22	44	62	93

311068 Keor SPE RT 1500 (1U) 1500VA / 1050W (PF = 0.7)

Load %			Int.batt.	Battery Cabinets (Mins)			
%	VA	W		BATTERY CABINETS N.A. FOR THIS MODEL			
10 %	150	105	71	-	-	-	-
20 %	300	210	32	-	-	-	-
30 %	450	315	19	-	-	-	-
40 %	600	410	12	-	-	-	-
50 %	750	525	9	-	-	-	-
60 %	900	630	7	-	-	-	-
70 %	1050	735	4	-	-	-	-
80 %	1200	840	4	-	-	-	-
90 %	1350	945	3	-	-	-	-
100 %	1500	1050	2	-	-	-	-

311069 Keor SPE RT 1500 (2U) 1500VA / 1200W (PF = 0.8)

Load %			Int.batt.	Battery Cabinets (311075) (Mins)			
%	VA	W		1	2	3	4
10 %	150	120	85	325	566	886	1100
20 %	300	240	42	159	308	446	574
30 %	450	360	26	103	205	308	395
40 %	600	480	18	76	128	219	301
50 %	750	600	12	57	106	169	228
60 %	900	720	9	48	90	118	189
70 %	1050	840	7	40	73	106	145
80 %	1200	960	4	31	59	94	114
90 %	1350	1080	4	27	53	82	106
100 %	1500	1200	3	24	48	69	96

311070 Keor SPE RT 2200 (2U) 2200VA / 1980W (PF = 0.9)

Load %			Int.batt.	Battery Cabinets (311076) (Mins)			
%	VA	W		1	2	3	4
10 %	220	198	52	117	199	303	358
20 %	440	396	28	73	115	167	224
30 %	660	594	17	46	77	108	139
40 %	880	792	12	30	54	81	105
50 %	1100	990	9	25	44	58	85
60 %	1320	1188	6	20	33	50	62
70 %	1540	1386	4	14	27	41	54
80 %	1760	1584	4	13	23	33	47
90 %	1980	1782	3	11	20	28	40
100 %	2200	1980	2	9	16	25	33

311071 Keor SPE RT 2200 (3U) 2200VA / 1980W (PF = 0.9)

Load %			Int.batt.	Battery Cabinets (311076) (Mins)			
%	VA	W		1	2	3	4
10 %	220	198	52	117	199	303	358
20 %	440	396	28	73	115	167	224
30 %	660	594	17	46	77	108	139
40 %	880	792	12	30	54	81	105
50 %	1100	990	9	25	44	58	85
60 %	1320	1188	6	20	33	50	62
70 %	1540	1386	4	14	27	41	54
80 %	1760	1584	4	13	23	33	47
90 %	1980	1782	3	11	20	28	40
100 %	2200	1980	2	9	16	25	33

311072 Keor SPE RT 3000 (2U) 3000VA / 2700W (PF = 0.9)

Load %			Int.batt.	Battery Cabinets (311077) (Mins)			
%	VA	W		1	2	3	4
10 %	300	270	89	213	336	476	585
20 %	600	540	42	96	155	227	304
30 %	900	810	25	58	99	130	195
40 %	1200	1080	17	44	70	100	118
50 %	1500	1350	10	31	54	78	100
60 %	1800	1620	8	26	45	59	83
70 %	2100	1890	6	21	36	52	65
80 %	2400	2160	4	17	29	45	56
90 %	2700	2430	4	13	26	38	50
100 %	3000	2700	3	10	22	31	44

311073 Keor SPE RT 3000 (3U) 3000VA / 2700W (PF = 0.9)

Load %			Int.batt.	Battery Cabinets (311077) (Mins)			
%	VA	W		1	2	3	4
10 %	300	270	87	208	331	466	577
20 %	600	540	41	95	153	225	302
30 %	900	810	25	58	99	128	193
40 %	1200	1080	16	44	70	100	117
50 %	1500	1350	10	31	54	78	100
60 %	1800	1620	8	26	45	58	83
70 %	2100	1890	5	21	35	51	65
80 %	2400	2160	4	17	28	44	55
90 %	2700	2430	4	13	25	37	50
100 %	3000	2700	3	10	22	30	44